


# 8891400 SERIES LED Mini Strobe



## Surface Mount

To +VDC (fuse @ 3A)  
TO Chassis Ground



### For Synchronization

1. Connect **YELLOW** wires of all heads together for synchronization (all heads must be set at the same pattern)

### For Simultaneous or Alternating Flash

1. Apply +VDC to **RED** and **YELLOW** wires simultaneously to enter Grouping Mode; lighthead will display short (single or double) flashers:
  - Single flash = Group 1
  - Double flash = Group 2
2. Remove **YELLOW** wire from +VDC and momentarily apply to +VDC to change Groups:
  - Heads in the same Group flash together.
  - Group 1 Heads alternate with Group 2 Heads

### For Flash Patterns

1. Momentarily apply +VDC to **YELLOW** wire:
  - Once for next pattern
  - Quickly three times for pattern Zero

**Note: Flash Pattern is preset to #0 Quint Flash**

#	FLASH PATTERN	#	FLASH PATTERN
0	Quint	6	Steady
1	8 Flash	7	Single
2	Single-Quad	8	Mega
3	Single H/L	9	Double
4	Single-Triple-Quint	10	Triple
5	Random	11	Quad


# 8891400 SERIES LED Mini Strobe



## Adhesive Mount


1. Select mounting location and clean surface
2. Peel one side of adhesive and apply to lighthouse base
3. Peel other side of adhesive and secure lighthouse firmly to the mounting surface

**Note: Optimum adhesive strength is achieved after 24 hours.**



## Screw Mount

1. Select mounting location.
2. Mark and drill mounting holes.
3. Secure lighthouse to mounting surface with supplied screws.



## Bracket Mount

1. Select mounting location.
2. Place rubber pad to bottom of lighthouse base
3. Place lighthouse to the mounting surface.
4. Align top holes of bracket onto the lighthouse base alignment points.
5. Secure lighthouse with supplied screws from the bottom of the bracket

