

11-626M Start•All® with AC Generator



Product Description

12/24 volt jump starting with NATO plug for heavy duty military vehicles and equipment. This unit will crank engines in cold weather climates time and time again. Plus the power of an AC generator to run power tools and lights to illuminate your work site.

Output

12/24 volt, 700/400 amp, 2750 watt AC Power, 24 volt NATO plug

Dimensions

31"W x 25"D x 29"H, 430 lbs.

Engine

Electric start, air cooled Briggs & Stratton Vanguard OHV gasoline engine with 2 gallon fuel tank

Cables & Clamps

30 ft., 1/0 ga. welding cable allows flexibility and ease of use, 1000 amp full-power clamps allow higher amperage flow

General Features

- NATO plug is polarity protected and live only in the 24 volt mode
- Electric start, air cooled Briggs & Stratton Vanguard OHV gasoline engine with 2 gallon fuel tank
- 30 ft., 1/0 ga. welding cable allows flexibility and ease of use
- 1000 amp full-power clamps allow higher amperage flow
- Volt and amp meter to monitor boosting output
- Voltage Control provides regulated voltage that is safe for vehicles and on-board electronics
- Reverse Current Shutdown Protection eliminates expensive repairs to the Start•All® if the unit runs out of gas
- Reverse Polarity Protection will not allow the Start•All® to be turned on if the cables are not hooked up correctly
- Polarity and low battery LED indicators confirm proper connections
- Anti-zap surge protection provides safer boosting
- Single DC boosting switch for easy operation