# **6 Function Receiver**

# **RECEIVER PART NUMBER**

9206RX 6 Function Receiver, with Master



# **CONTENTS**

1 x Receiver

1 x Instructions

### **Compatible Transmitters**

Standard 92106TX ΙP 92206TX Slim 92306TX Χ 92506TX

#### **RECEIVER SPECIFICATION**

#### **ELECTRICAL**

Voltage Nominal 12/24V DC 8 to 36V DC Voltage Min/Max

Switch Type MOSFET (Positive Switching)

Modulation 2-GFSK. Gaussian Frequency Shift Keying 433.050 MHz to 434.790 MHz

Frequency 902.025 MHz- 927.975 MHz

32

Channels **Channel Selection** Fixed

Channel hopping

Fixed Receiver Technology

-40° C to + 70° C (-40° F to + 158° F) Temperature Range

60m (200ft) Range

# **CURRENT CAPACITY**

**FET Rating** 10A System Rating 10A

**Quiescent Current** 31mA 12V/17mA 24V on Standby (Not SET)

Overload Protection (Auto Shutdown) 10A

**AERIAL** 

Internal Antenna Supplied and fitted Yes

External Antenna AC9860/ AC9861/ AC9862/ AC9863 & AC9869 - order separately Optional

**OUTPUTS** 

Master Yes Parallel or Continuous Function Supply to Receiver is switched 6

**CONFIGURATION** 

For programming interlocks, push/push latch, parallel master inhibit, timeout, channel timeout delay, **RS232 Programming** Yes to users' requirements

master on delay, radio button de-latching and output allocation.

**PERFORMANCE** 

Simultaneous Outputs Programable (Modify through configuration) Yes Instant TX response Yes Programable (Modify through configuration)

**DIAGNOSTICS** 

LED's Yes Confirm 5 Volts, SET, Fault and all Outputs.

#### **PROTECTION**

Back EMF Yes Diode protection on all outputs

Registration codes Yes Over 16 million

STOP Connection Yes Internal Emergency Stop Connection


WIRING

Wiring Loom Yes 3 metres (10ft) supplied and fitted

Cable Gland Yes Supplied and fitted

Connections Screw terminal into plug and socket on PCB, for easy "swap out"

# **ENCLOSURE**



Weight 0.3 lbs (335gms)

Lid Clear PC/FR V0 and UV stabilised Base Black PC V0 and UV stabilised

Breather Gortex fitted in base
Mounting 4 external lugs

Fixings 5mm (3/16") not supplied

IP Rating IP55

92 Series			9206RX
BUILD SPECIFICATION TABLE FOR MODELS IN THIS RANGE			
Ident	Legend	Connection	6
	+ - F1 F2	Positive, Negative, F1 and F2	S
	F3 F4 F5 F6 M	F3, F4, F5, F6 and Master	S
	ST -	STOP and -	S
	S+ S-	S+ S-	S
	ANT	Internal Antenna	S
X5		SMA Connector (external antenna)	S
LK1	Р	Master - Parallel	С
LK2	С	Master – Continuous	С
LK3	RS232	RS232	S
		3 metres 2 core	S
		3 metres 7 core	S
		9804 Lo-Cover	S
		9802 Lo-Cover	

S = Standard. C = Customer configured (see "Factory Settings").

 +
 Positive
 8-36V supply

 Negative
 0 Volts

 F1 to F6
 Outputs to F1 through F6

M Master Output

STOP - STOP, when grounded shuts down the Receiver S+S- Master Secondary for Safety solenoid connections etc.

ANT Blade connector for internal antenna

SMA Aerial connection for optional external antenna (internal antenna must be removed)

LK1 Master Selection by Jumper (Parallel)
LK2 Master Selection by Jumper (Continuous)

Factory Settings 418/915MHz configured Parallel, 433.92MHz configured Continuous RS232 RS232 for Wired Remote and interface to access special programmes

### COMPLIANCE

REG 10 EC Type-approval mark E11 037601

EC Type-approval No: e11/72/245\*2009/19\*7601\*00

FCC FCC CFR 47 Part 15.109

433.050MHz to 434.790MHz FCC CFR 47 Part 15.109 902.025MHz to 927.975MHz

IC ICES-003 Issue 6.

433.050MHz to 434.790MHz

ICES-003 Issue 6.

902.025MHz to 927.975MHz

CE RED Directive

ETSI EN 300 220-2 v3.2. ETSI EN 300 220-1 v3.1.1. ETSI EN 301 489-17 V3.1.1, ETSI EN 301 489-1 V2.1.1 433.050MHz to 434.790MHz

Australia/NZ ETSI EN 300 220-2 v3.2.1

ETSI EN 301 489-1 V2.1.1 433.050MHz to 434.790MHz 915.025MHz to 927.975MHz

RoHS Directive 2011/65/EU